



4 Channel Bridgeable Amplifier

General

Max.power output	80 W x 4 (4 Ω) 130 W x 4 (2 Ω) 260 W x 2 (4 Ω Bridged)
RMS power output	40W x 4 (4 Ω) 65 W x 4 (2 Ω) 130 W x 2 (4 Ω Bridged)
Frequency Response	10 Hz to 70 kHz
Impedance	2 Ω to 8 Ω
Total Harmonic Distortion(THD)	<0.05%
S/N Ratio	94 dB
LPF	80Hz
HPF	40Hz-500Hz
RCA Terminals	4ch
Speaker Terminals	Screw-type
Input Level control	300mV - 6.5 V